

PiggyBack™ Tank Anode Rectifier with Continuous DC Output Adjustment for Easier Setup

Although this rectifier can be used for many CP applications, we have specifically designed it with our PiggyBack Tank Bottom Anode System in mind. This unit can be customized if required. (30 VDC is sufficient for PiggyBack.)

Features:

- Continuous DC Voltage Adjustment over output range
- Magnetic Circuit Breakers for Primary & Secondary side of transformer
- Magnetic Circuit Breaker for DC output
- Heavy AC / DC Lightning and Surge Protection
- Separate DC output Volt Meter & Ammeter
- NEMA 3R Air Cooled Galvanized Powder Coat Housing
- See Wiring Diagram for UL/CSA listed Components
- Suitable for Wall or Pole Mount



18"wide x 11"deep x 20"high – 55lbs

Rectifier – Model Number Example: REC-120/240VAC-1PH50/60-30V-3A-CADJ

Example Codes:

REC = Rectifier Product Category

120/240VAC = Dual Input (choose factory wired 120/240 or 240/120)

1PH50/60 = Single Phase 50 / 60 Cycle

30V = 30-Volt DC Output

3A = 3-Ampere DC Output **Choose from** 3, 5, 10 or 15 Amp

CADJ = Continuously Adjustable DC Output